

Effective from 17th March, 2020



Dear Customer

In preparation for a forced shut down of your post mix equipment, the following steps are to be taken:

Shut Down

Back End

1. Turn the equipment off at the electrical supply.
2. Turn your CO2 supply to equipment off.
3. Turn off the water supply to the post mix equipment

Front End

1. In line with daily cleaning procedures, clean nozzles/diffusers & wipe down in accordance to cleaning guide and replace. These cleaning instructions can be found in your Coca-Cola Cleaning Kit.

Re Start

(If not more than 30 days from shut down follow the below process)

Front End

1. In line with daily cleaning procedures, clean nozzles/diffusers & wipe down in accordance to cleaning guide and replace prior to restarting. These cleaning instructions can be found in your Coca-Cola Cleaning Kit.

Back End

1. Check Bag- In-Box best before date and change syrup if required.
2. Turn the water supply to the equipment on.
3. Turn your CO2 supply to equipment on.
4. Turn the equipment on at the electrical supply.
5. Flush through 2 litres, or 4 pints of each brand
6. Carry out a taste test and ensure carbonation levels are acceptable.
7. Return to normal use. If any issues contact CCEP for Service (0800 1000 000)